

# 3D PTZ Controller



## KBD505 Specs

Dome type	SpeedDome Keyboard Controller Specification	
	KBD 505	
Function Specification	Dome camera or decoder address setting range 0~9999	
	Users can set password, keyboard locking time, communication rate and protocol by using the operation menu.	
	Functions controlling the dome camera : such as camera background light compensation on/off .	
	Operate the dome camera at different speed setting, speed switching smooth and stable	
	Control the pan tilt auto line scan, speed and direction can be set as well	
	Set or call the set points and cruise tracks of the dome camera. Altogether 999 preset points and 1--6 cruise tracks can be set. Each track involves 16 preset position and the dwelling time and call speed upon each	Set or call the set points and cruise tracks of the dome camera. Altogether 128 preset points and 1--6 cruise tracks can be set. Each track involves 17 preset position and the dwelling time and call speed upon each
	Manually or automatically control the dome camera, and change the internal function settings of particular camera by call the menu of the camera.	
	Manually control the focus, zoom and iris of the camera.	
	Provide on line control help	
Intelligent design, easy operation, all setting can be done with the operation menu,non need restart the keyboard.		
Joystick	3D(Pan/Tilt,Zoom)	2D(Pan/Tilt)
Communication	RS-485/RS-232(PC) Baudrate: 2400bps~19200bps	
Communication Distance	1200m	
Connection	RJ45 Cable	
Power	DC12V 900mA/DC9V 1000mA Consumption: 5W	
Weight (Kg)	1.2Kg	
Dimensions(mm)	95mm(H)X205mm(L)X205mm(W)	